

Product Name

Electric Exit Signs

Associated Specification Section

Section 10425 - Signage

Manufacturer's Name

Seton Identification Products Inc., (AEC)



Page 1

2003-02-26

PRODUCT DESCRIPTION**PRODUCT FEATURES**

- BASIC USES / RELATED USES
 - Electric exit signs, with emergency lighting and battery backup.
 - Perimeter LED exit signs.
- PRODUCT ATTRIBUTES AND CHARACTERISTICS
 - LED Exit Signs: Use only 1.8 watts of AC power, 90 minute nickel cadmium battery backup, white or black housing.
 - Combination Exit Sign and Emergency Light:
 - Emergency lighting: 8 watt sealed beam or 6 wall HIT lamps.
 - Lead calcium battery backup which automatically recharges.
 - Ceiling or surface mounted housing.
- SELECTION CRITERIA
 - LED Exit Signs: Provide up to 10 years maintenance free service.
- APPLICABLE STANDARDS, RELATED REFERENCES
 - UL 924 - Emergency Lighting and Power Equipment.
- QUALITY STATEMENT, TESTS, CERTIFICATIONS, AND APPROVALS
 - L.E.D. Exit Signs: UL 924 Listed.
 - Combination Exit Sign and Emergency Light: UL Listed.
- PACKAGING, HANDLING, PROTECTION, AND DELIVERY INSTRUCTIONS
 - [identify special concerns only, over-size loads, over-weight loads, available in long lengths only, etc]

PRODUCT PROPERTIES

- COMPONENTS
 - Perimeter L.E.D. Exit Sign:
 - Housing: Steel, painted, black or white enamel finish, red or green lens.
 - Power: 120/277 VAC dual voltage transformer.
 - Battery: Nickel cadmium type, 90 minute operation upon power failure.
 - Combination Exit Sign and Security Light:
 - Cabinet: 20 gauge steel, painted white, ceiling or surface mounted.
 - Lettering: Cut out of cabinet, with red and green lettering panels behind.
 - Power: 120/277 VAC dual voltage transformer.
 - Lighting:

* 8 watt Par-36 sealed beams, with metal holder.

Product Name

Electric Exit Signs

Associated Specification Section

Section 10425 - Signage

Manufacturer's Name

Seton Identification Products Inc., (AEC)

**PRODUCT DESCRIPTION**

- * 6 watt rectangular HIT lamps, with plastic holder.
- Battery: Sealed lead calcium battery, automatically recharges when connected to power supply.
- DIMENSIONS
 - L.E.D. Exit Sign: 310 x 190 x 64 mm (12-1/4 x 7-1/2 x 2-1/2 inches).
 - Exit sign with 8 watt sealed beams: 648 x 330 x 127 mm (25-1/2 x 13 x 5 inches).
 - Exit sign with 6 watt lamps: 318 x 330 x 127 mm (12-1/2 x 13 x 5 inches).

PRODUCT PLACEMENT

- PREPARATION
 - Clean surface prior to applying signage.
 - Establish position as angle, plumb or level.
- INSTALLATION
 - Mechanically fasten to ceiling or wall, using supplied hardware.

Corporate Identification

Seton Identification Products Inc., (AEC)
20 Thompson Road, P.O. Box 819, Brantford CT 06405-089
4451 Eucalyptus Avenue, Suite 330, Chino CA 91790

Phone: 1-800-243-6624

Fax: 1-800-345-7819

On-line Ordering: 1-800-571-2596 (7:00 am to 9:00 pm EST/EDT)

Web home page URL: www.seton.com**Technical Services Available**

Architects: Product binder, specifications on disk and available on Seton web site..

Contractors: Submittal binder.

Classification and Filing

MasterFormat:

Section 10425 - Signage

UniFormat:

Product Name

Electric Exit Signs

Associated Specification Section

Section 10425 - Signage

Manufacturer's Name

Seton Identification Products Inc., (AEC)



Page 3

2003-02-26

PRODUCT DESCRIPTION

Not Applicable

END OF PRODUCT DESCRIPTION